

Wall Plate BT Audio Amplifier

250 Watts Peak Power

Model: VRWPA84BT



Made in Taiwan

What's Included:

● Amplifier

● Wall Plate

● Adapter

● Screws

● User Manual



FCC Certified



Website: www.vaiyer.com



Customer Support: sales@vaiyer.com

Wall Plate Audio Amplifier with Bluetooth v5.0

FEATURES:

- Bluetooth v5.0 with aptX
- 45W Class-D High-Quality Power Amplifier
- Compact Wall Plate Design
- Easy Installation

SPECIFICATIONS:

- Audio Inputs: Bluetooth Receiver or Stereo Audio Line-Level Input
- Bluetooth Version: Bluetooth v5.0 Compatible with aptX
- Bluetooth Range: Up to 30 Meters (Open Space)
- Power Amplifier Type: Stereo Class-D
- Minimum Load Resistance: 4Ω
- Output Power: $2 \times 45W$ RMS per Channel (@ $RL = 4\Omega$)
- THD+N: 0.1% (@ $RL=4\text{ ohm}$, $f = 1\text{ kHz}$)
- Minimum Load Resistance: 4Ω
- Includes Speaker Protection Circuit
- Power Source: 24 VDC
- 3-Minute Link-Lost Timeout Function (Bluetooth Automatically Switches to Pairing Mode if Reconnection Fails)
- Audio Priority: Bluetooth > AUX Input

CONNECT AND OPERATE

STEP 1: Install the Unit in the Wall and Connect the Power and Speaker Cables.

STEP 2: Turn the Rotary Switch to Power On the Unit.

STEP 3: The Bluetooth Status LED Will Blink Rapidly in Pairing Mode, Connect Your Bluetooth Device to the Audio Amplifier.

STEP 4: For AUX Input, Connect an Audio Cable and Start Playback.
The Unit Will Automatically Switch Between Bluetooth and AUX Input

